

**ELECTRICAL POWER DATA** (ALL FIGURES ARE TYPICAL AND ASSUME STANDARD ELECTRONIC CONTROL GEAR)

**Discharge Lamps**

Lamp	Wattage	Total Circuit Watts
CDM-T Ceramic Discharge	35W	42
	2x35W	85
	70W	78.5
	2x70W	TBC
	150W	163
CDM-TC Ceramic Discharge Capsule	20W	24
	35W	42
	2x35W	85
	70W	78.5
	2x70W	TBC
CDM-Tm Mini Master Colour	20W	25
CDM-TP Ceramic Discharge Protected	70W	78.5
	150W	163
CDM-TD Ceramic Discharge Double Ended	70W	78.5
	150W	163
SDW-TG Mini White SON	50W	60
	100W	108

**Linear Fluorescent**

Lamp	Wattage	Total Circuit Watts	Wattage	Total Circuit Watts
TL5 (HE)	14W	18	2x14W	30
	21W	25	2x21W	46
	28W	33	2x28W	61
	35W	40	2x35W	76
			3x14W	47
			4x14W	62
TL5 (HO)	24W	28	2x24W	49
	39W	45	2x39W	86
	54W	61	2x54W	120
	49W	56	2x49W	109
	80W	88	2x80W	172
			3x24W	76
			4x24W	99
T8	18W	19	2x18W	37
	36W	37	2x36W	70
	58W	56	2x58W	107
	70W	68	2x70W	129
			3x18W	54
			4x18W	70

**Compact Fluorescent**

Lamp	Wattage	Total Circuit Watts	Wattage	Total Circuit Watts
TC-S (4 pin)	5W	5.3	9W	8.5
	7W	7	11W	12
TC-D (4 pin)	10W	12	2x13W	28
	13W	14	2x18W	38
	18W	18	2x26W	54
	26W	26		
TC-T (4 pin)	13W	14	2x13W	28
	18W	18	2x18W	38
	26W	26	2x26W	54
	32W	35	2x32W	70
	42W	46	2x42W	92
	57W	62		
TC-L	18W	19	2x18W	37
	24W	25	2x24W	52
	36W	37	2x36W	70
	40W	44	2x40W	84
	55W	58	2x55W	113
	80W	88	2x80W	172
2D (4 pin)	16W	15.2	38W	39.7
	28W	28.7		
TL5 (Circular)	22W	25	55W	60
	40W	43.5	60W	65

